

NGX CASSETTE TRANSITION 24FO BASE-8 MPO-LC - **NGXCA01Q**



Browse on Mobile

 Browse on Web

NEXCONEC[®] TRANSITION NGX cassettes are pre-terminated modules MTP/MPO-LC fanouts that are suitable for up to 40G/100G applications to interconnect backbone with discrete connections. The NGX cassettes are designed to easy plug into NEXCONEC NGX 1U 6 slot panel. The MPO and single ferrule connectors are available in Standard and Elite versions to cater customer's power budget requirements. For the 24 Fibers 40G to 10G version, each cassette holds 3x 8f MPO-LC fanouts.

FEATURES

- ✓ Conform to IEC, EIA-TIA, and Telcordia performance requirements
- ✓ Shuttered dust proof LC adapters
- ✓ Available in standard Single mode and Multimode fiber options
- ✓ Available in 40G to 10G and 100G to 25G transition
- ✓ Available in Polarity A/B/C as per TIA/EIA-568-C.3
- ✓ RoHS, REACH & SVHC compliant, Materials Conflict compliant
- ✓ Flame retardant ABC+PC material



APPLICATIONS

- ✓ Telecommunication networks
- ✓ Data centers, Co-location DC
- ✓ LAN or Campus Wide Network
- ✓ Broadband network
- ✓ Supports SFP, QSFP, CFP applications
- ✓ 100G to 25G/ 40G to 10G transition


SPECIFICATIONS

Parameters	Units	SM MPO	SM LC	MM MPO	MM LC
Avg/Max IL – Standard	dB	≤ 0.25/0.75	≤ 0.20/0.30	≤ 0.60	≤ 0.18/0.30
Return Loss (PC/APC)	dB	≥ 60	≥ 60/65	NA	NA
Avg/Max IL– Premium	dB	≤0.10/0.35	≤ 0.12/0.15	≤ 0.10/0.35	≤ 0.12/0.15
Return Loss (PC/APC)	dB	≥ 60	≥ 60/65	NA	NA

ORDER INFORMATION

Product	Part Number	Product Description
	NGXCA01Q	NGX Transition Module 40G-10G 24FO SMF OS2 LC - 3xMPO(M) Elite 8FO
	NGXCA02Q	NGX Transition Module 40G-10G 24FO MM OM3/OM4 LC - 3xMPO(M) Elite 8FO

RELATED PRODUCTS AND ACCESSORIES

Product	Part Number	Product Description
	NGXPP01	1U 6 Slots NGX Modular Patch Panel Unloaded

	<p>NGXPP02</p>	<p>1U 6 Slots NGX Angled Modular Patch Panel Unloaded</p>
	<p>NGXPP03</p>	<p>1U 6 Slots NGX Hybrid Modular Patch Panel Unloaded</p>
	<p>NGXPP04</p>	<p>NGX Hybrid Angled Modular Chassis 1U Fiber/Copper (6 Fiber NGX Slots / 12P KJ) Unloaded</p>
	<p>NGXPP21</p>	<p>2U 12 Slots NGX Modular Patch Panel Unloaded</p>
	<p>NGXBK01</p>	<p>Zero RU NGX Bracket, 3 Slots Unloaded</p>